




QUICK
START
GUIDE



WHAT'S IN THE BOX




THE FRONT



- 1 FN Locking Mode 2 12 Multimedia & Internet Hotkeys 3 One-Touch 4 Hotkeys
4 Multi-Device Switch 5 Operating System Swap 6 PC/MAC Dual-Function Keys

THE BOTTOM




CONNECTING BLUETOOTH
DEVICE 1 (For Mobile Phone/Tablet/Laptop)




- 1: Short-press FN+7 and choose Bluetooth device 1 and light up in blue.
Long-press FN+7 for 3S and blue light flashes slowly when pairing.
2: Choose [A4 FBK23 AS] from your Bluetooth device.
The indicator will be solid blue for a while then light off after the keyboard is connected.

CONNECTING BLUETOOTH
DEVICE 2 (For Mobile Phone/Tablet/Laptop)




- 1: Short-press FN+8 and choose Bluetooth device 2 and light up in green.
Long-press FN+8 for 3S and green light flashes slowly when pairing.
2: Choose [A4 FBK23 AS] from your Bluetooth device.
The indicator will be solid green for a while then light off after the keyboard is connected.

CONNECTING BLUETOOTH
DEVICE 3 (For Mobile Phone/Tablet/Laptop)



- 1: Short-press FN+9 and choose Bluetooth device 3 and light up in purple.
Long-press FN+9 for 3S and purple light flashes slowly when pairing.
2: Choose [A4 FBK23 AS] from your Bluetooth device.
The indicator will be solid purple for a while then light off after the keyboard is connected.

CONNECTING 2.4G DEVICE



- 1 Plug the receiver into the computer's USB port.
2 Use the Type-C adaptor to connect the receiver with the computer's Type-C port.
3 Turn on the keyboard power switch.
Yellow light will be solid (10S).
The light will be off after connected.


OPERATING SYSTEM SWAP

Windows / Android is default system layout.

System	Shortcut [Long-Press for 3S]	Device / Layout Indicator
iOS	fn + I ios	Light will be off after flashing.
Mac	fn + O mac	
Windows & Android	fn + P w/a	

Note: The layout you used last time will be remembered. You can switch the layout by following the above step.

INDICATOR (For Mobile Phone/Tablet/Laptop)




Indicator	Yellow Light	Blue Light	Green Light	Purple Light
Multi-Device Switch	fn + I ios	fn + & 7 C3	fn + * 8 C3	fn + I 9 C3
Device Switch: Short-Press for 1S	Solid Light 5S		Solid Light 5S	
Pair Device: Long-Press for 3S	No Need to Pair		Pairing: Flashes Slowly Connected: Solid Light 10S	


ANTI-SLEEP SETTING MODE

Note: Supports 2.4G Mode Only

To prevent your PC from entering the sleep-mode setting while you are away from your desk, simply turn on our new Anti-Sleep Setting Mode for PC. It will automatically simulate the cursor movement once you turn it on. Now you may take an hour nap while downloading your favorite movie.




ONE-TOUCH 4 HOTKEYS



FN MULTIMEDIA KEY COMBINATION SWITCH

FN Mode: You can lock & unlock FN mode by short pressing FN + ESC by turn.

- 1 Lock Fn Mode: No need to press FN key
2 Unlock Fn Mode: FN + ESC
After pairing, FN shortcut is locked in FN mode by default, and the locking FN is memorized when switching and shutting down.



OTHER FN SHORTCUTS SWITCH

Shortcuts	Windows	Android	Mac / iOS
fn + backspace		Screen Lock	Screen Lock (iOS Only)
fn + delete		Pause	
fn + up arrow		Device Screen Brightness +	
fn + down arrow		Device Screen Brightness -	

Note: The final function refer to the actual system.

DUAL-FUNCTION KEY

Multi-System Layout

Keyboard Layout	Windows / Android (W / A)	Mac / iOS (mac / ios)
fn + I ios, O mac, P w/a	Switching Steps: 1 Choose iOS layout by pressing FN+I. 2 Choose MAC layout by pressing FN+O. 3 Choose Windows / Android layout by pressing FN+P.	
ctrl	Ctrl	Control ^
opt	Start	Option
alt	Alt	Command
cmd	Alt-Right	Command
ctrl	Ctrl-Right	Option

LOW BATTERY INDICATOR



Flashing Red light when the battery is below 10%.

SPECIFICATIONS

- Connection: Bluetooth / 2.4GHz
Multi-Device: Bluetooth x 3, 2.4G x 1
Operation Range: 5-10 m
Report Rate: 125 Hz
Character: Laser Engraving
Includes: Keyboard, Nano Receiver, 1 AA Alkaline Battery, Type-C Adaptor, USB Extension Cable, User Manual
System Platform: Windows / Mac / iOS / Chrome / Android / Harmony OS...

Q & A

- Question: How to switch layout under different system?
Answer: You can switch layout by pressing FN + I / O / P under Windows | Android | Mac | iOS.
- Question: Does the layout can be remembered?
Answer: The layout you used last time will be remembered.
- Question: How many devices can be connected?
Answer: Interchange and connect up to 4 devices at the same time.
- Question: Does the keyboard remember the connected device?
Answer: The device you connected last time will be remembered.
- Question: How can I know the current device is connected or not?
Answer: When you turn on your device, the device indicator will be solid. (disconnected: 5S, connected: 10S)
- Question: How to switch between connected Bluetooth device 1-3?
Answer: By pressing FN + Bluetooth shortcut (7 - 9).

WARNING STATEMENT

The following actions may damage the product.

1. To disassemble, bump, crush, or throw into fire is forbidden for the battery.
2. Do not expose under the strong ultraviolet or high temperature.
3. The discard of battery should obey to the local law, if possible please recycle it.
Do not dispose it as household garbage, because it may cause an explosion.
4. Do not continue to use if severe swelling occurs.
5. Please do not charge the battery.

